


Sujetacables DIN-741

Cincado

Hierro fundido

Ø Diámetro cable
 L Altura sujetacables
 A Ancho sujetacables
 I Distancia entre centros
 D Métrica
 B Espesor sujetacables



Cotas en milímetros (mm)

Ø	2-3	4-5	6	7-8	10	12	14	16	19	22
D	M4	M5	M5	M6	M8	M10	M10	M12	M12	M14
A	21	24	26	30	37	44	46	52	58	64
B	10	11	12	14	20	25	25	28	32	35
C	10	10	11	15	19	23	25	28	34	35
I	9	11	13	16	20	25	27	30	34	38
L	20	24	28	34	42	55	57	63	75	85
Ø	26									
D	M14									
A	68									
B	38									
C	38									
I	42									
L	92									